

### • Description

This sensor is Lead-Free and designed for the measurement of O<sub>2</sub> concentration in gas phase. It can be used as the pin-to-pin replacement of the standard 4-series electrochemical O<sub>2</sub> sensors made by the other manufacturers.

### • Performance Characteristics

Nominal Range:	0~25 %vol oxygen
Maximum Overload:	30 %vol oxygen
Sensitivity (20 °C):	100 ± 20 µA in air
Response Time (T90):	≤ 15 s
Baseline:	±0.5%vol oxygen @20 °C
Detections limit:	0.1 %vol oxygen
Linearity:	The error is < ± 5 %FS or <0.3 %vol, whichever is the less.
	Theoretical formula: $K \cdot \ln(1/(1-c))$
Bias Voltage:	-600 mV
Warm up time:	Reading returns to within 21 %vol in air after losing bias voltage for 15 mins
Repeatability:	< ± 5 %

### • Environmental

Temperature Range:	-40°C ~ 50°C
Pressure Range:	1 ± 0.1 atm
Humidity Range:	15% ~ 90%RH non-condensing

### • Life Time

Long Time Output Drift:	< 5 % /year
Recommended Storage Temp:	10°C ~ 30°C
Expected Operating Life:	5 years in clean air
Storage Life:	12 months in original packaging
Warranty:	36 months


### • Physical Characteristics

Housing Material:	ABS
Weight (Nominal):	5 g
Orientation:	Any
RoHS Compliance:	RoHS Compliant

### • Installation

Output signals from the sensor pins are different. Inappropriate use of the pins in product design will affect the sensor functionality. Exposure to high concentrations of solvent vapors should be avoided under any condition. Mechanical overstress may cause deformation or cracks of the plastic enclosure of the sensor. If the sensor is used in extreme environmental conditions, please contact us for more details.

### • Product Dimensions



All dimensions in mm

All tolerances ± 0.10 mm unless otherwise stated

### • Note


The performance data in this document are conducted by using SemeaTech recommended test circuitry and test environment at 20°C, 50 %RH and 1 atm. Sensor performance varies under different environmental conditions. Please contact us if you need more details.



## ELECTROCHEMICAL O2-LF SENSOR(4 SERIES) (P/N:053-0000-000)

[illegible]

Note: The cross sensitivities include but not limited to the above gases. It may also respond to other gases. The data in the table above may vary from different batches of sensors and the changes of test environment. Calibration using the gases that have the cross sensitivities to this sensor is not recommended.



This sensor is designed to be used in certain instruments for life critical applications. To ensure the sensor functioning per its specifications inside the instrument, it is required to read the instrument user's guide carefully and comply with the calibration procedures by using certified target calibration gas before each use. Failure to do so may cause serious injury and fatality. Please do not open the sensor plastic enclosure because the electrolyte and other chemicals stored inside are harmful.

It is highly recommended for customers to validate the sensor performance using the document as a reference for their product designs or applications.

This product data sheet is used for reference only.

SemeaTech is committed to provide its customers the most accurate data based on its best knowledge. SemeaTech does not provide product warranty for failures of using its products in accordance with product specifications that are described in the data sheet, or other misuse, abuse, negligence to the product.